



(19)

Generated Document

(11) Publication number: **02155424 A****PATENT ABSTRACTS OF JAPAN**(21) Application number: **63178230**(51) Int. Cl.: **H02H 7/122 G01R 19/165 H02M 1/00**
H02M 7/48(22) Application date: **19.07.88**

(30) Priority:

(43) Date of application publication: **14.06.90**

(84) Designated contracting states:

(71) Applicant: **HITACHI SEIKO LTD**
(72) Inventor: **SHINADA TSUNEO**
(74) Representative:**(54) PROTECTOR FOR
INVERTER CONTROLLED
POWER SUPPLY**

(57) Abstract:

PURPOSE: To improve response properties of an apparatus by providing a reactor with air-core coil connected in series between DC power supply and inverter part and an overvoltage sensing circuit outputting a signal, only when a voltage generated in a secondary winding

magnetically combined with said reactor exceeds a predetermined value and is generated continuously for the period of time longer than predetermined one.

CONSTITUTION: When an overvoltage flows through a reactor 14 by a malfunction of inverter part 4, a voltage corresponding to di/dt is generated in a reactor secondary winding 15. Because said voltage can obtain sufficiently large output even via no amplifier, it is possible to compare the voltage as it is with a set value by a comparator 19. When said voltage generated in the reactor secondary winding 15 exceeds a set value corresponding to $\epsilon \cdot utri; di/dt$ a signal is outputted from said comparator 19 to an ON-delay timer circuit 20 and when said state continues longer than a set time, a signal is outputted from said ON-delay timer circuit 20 to an inverter controlling circuit 9 to stop the switching operation of transistors T1-T4.

COPYRIGHT: (C)1990, JPO&Japio



